

# Remote Annunciator (Repeater Panel)

## SureFIRE RP

SureFIRE RP - RS485 Based repeater panel makes it a cost effective accessory to SureFIRE range of Multi-Zone Fire Alarm Panels. This user friendly product offers flexibility and reliability.

Easy installation and commissioning will allow the installer to meet the end-user demands. For end-users, clearly visible LCD display and easy to operate Key functions make simple and unambiguous utilization of the product.



### Mechanical

<b>Dimensions</b>	120 (W) x 120 (D) x 40(H) mm
<b>Weight</b>	490 grms
<b>Construction</b>	22g metal enclosure with SG PC
<b>Operating Temp</b>	+5°C to 50°C
<b>Relative Humidity</b>	90% to 95% RH non-condensing

### Specification

#### Power Supply

Regulated 24/12V DC

#### Inputs

RS-485 Communication from SureFIRE series of Multi-Zone FAP

#### Outputs

16x2 Character LCD Display  
Common LED Status indication  
Local Buzzer to indicate the zone faults

### Features

- Microprocessor controlled, user friendly design
- Flexible System Architecture Compatible with SureFIRE 8F- 32F
- RS-485 Communication allows instantaneous indications
- Compact in size unlike conventional repeater panel
- Local Audible alarm along with LCD message
- Easy silencing of audible alarm by 'Silence' key

### Dimensional Diagram

All Dimensions are in mm

